

Fakultet tehničkih nauka, DRA, Novi Sad

Predmet:

Struktura i organizacija baza podataka


**Prevodenje ER modela u relacioni
model**


Dr Slavica Kordić,

Vladimir Dimitrieski,


Nikola Obrenović

Primer prevodenja





SCADATacka({STSifra, STIme, Vrsta, Vrednost, TipVred},
{STSifra})



$\text{Senzor}(\{\text{STSifra}\}, \{\text{STSifra}\})$


$\text{Aktuator}(\{\text{STSifra}, \text{Aktivan}\}, \{\text{STSifra}\})$

$\text{Senzor}[\text{STSifra}] \subseteq \text{SCADATacka}[\text{STSifra}]$

$\text{Aktuator}[\text{STSifra}] \subseteq \text{SCADATacka}[\text{STSifra}]$

$\text{SCADATacka}[\text{STSifra}] \subseteq \text{Senzor}[\text{STSifra}] \cup \text{Aktuator}[\text{STSifra}]$


$\text{Senzor}[\text{STSifra}] \cap \text{Aktuator}[\text{STSifra}] = \emptyset$



IstorijaMerenja({STSifra, Vreme, IstMerenje},
{STSifra+Vreme})

IstorijaMerenja[STSifra] \subseteq Senzor[STSifra]

Senzor[STSifra] \subseteq IstorijaMerenja[STSifra]




UdaljenaJedinica({UJSifra, UJIme,Protokol}, {UJSifra})

SCADATacka({STSifra, ST_Ime, Vrsta, Vrednost, TipVred, UJSifra}, {STSifra})

Null(SCADATacka,UJSifra) = ⊥

SCADATacka[UJSifra] ⊆ UdaljenaJedinica[UJSifra]

UdaljenaJedinica[UJSifra] ⊆ SCADATacka[UJSifra]



CentralnaJedinica({CJSifra, OS, AppSW}, {CJSifra})

Komunicira({UJSifra, CJSifra, Medium}, {UJSifra+CJSifra})

Komunicira[UJSifra] ⊆ UdaljenaJedinica[UJSifra]

UdaljenaJedinica[UJSifra] ⊆ Komunicira[UJSifra]

Komunicira[CJSifra] ⊆ CentralnaJedinica[CJSifra]